



Product Type: Controllers

ASC/3 Inverted Pedestrian Calls

(Reference ASC/2 WPT 0x002 Bit 3)

Reference: AN2055
Date: March 16, 2007

Invert pedestrian detector inputs to allow dead-man (no input will call)

MM-1-8-1: Disable ("D") LP step X
Where "X" is an open LP step 1-100

MM-1-8-2 Program LP steps as follows:

```
LP X
IF    PED DETECTOR      1 IS ON

THEN SET PED DET       1  OFF

ELSE  SET PED DET       1  ON
-----
```

MM-1-8-1: Enable ("E") LP step X

A separate LP statement will be required for each phase that requires this feature.